# CUSTOMER PRODUCT SPECIFICATION SHEET

(RoHS Compliant


## CABLE 355 RF: RF CABLE ASSEMBLY, I-PEX MHF IV PLUG + STRAIGHT SMA BULKHEAD JACK + 0.81MM CABLE - 6GHz


### SPECIFICATIONS:


- 1. I-PEX MHF IV PLUG, P/N: 20448-001R-081
- 2. 0.81 COAXIAL CABLE, COLOR: GRAY
- 3. SMA STRAIGHT BULKHEAD JACK, GOLD, P/N: RFCT-SMA049-F08.


#### NOTES:

- 1. THE ORIENTATION OF CONNECTORS ON DRAWING IS FOR REFERENCE ONLY, IF THE ORDER IS LEFT BLANK THE CONNECTOR WILL NOT HAVE FIXED ORIENTATION.
- 2. FIXED ORIENTATION IS SUGGESTED FOR CABLE LENGTH 25M TO 100MM. PLEASE SPECIFY THE FIXED ORIENTATIONS FROM THE ORDER CODE (F1, F2, ETC)
- 3. CONTACT GRAD CONN IF THE ORIENTATION YOU REQUIRE IS NOT SHOWN.
- 4. WORKING FREQUENCY RANGE: DC-6GHz.
- 5. OPERATING TEMPERATURE: -40°C~+85°C
- 6. IMPEDANCE: 50 OHM










SMA JACK DETAIL DIMENSION

RECOMMENDED SMA MOUNTING HOLE



#### HOW TO ORDER

CABLE 355 RF - X X X - X X - X WASHER AND NUT OPTIONS:
"L" LENGTH IN MM

eg: 100MM = 100

A = ASSEMBLED WITH CONNECTOR

(MIN. = 025, MAX. = 400 ORIENTATION OPTIONS: STANDARD = 100, 150, 200)

Tolerance: <50mm: +2mm.

51-200mm: ±5mm.

201-400mm: ±7mm.

BLANK = DOES NOT HAVE A FIXED ORIENTATION F1 = MHF CONNECTION DOWN (L=25-220MM)

F2 = MHF CONNECTION UP (L=25-220MM)

(SEE NOTES 1. 2, 3 AND DIAGRAMS FOR MORE INFORMATION)

Scale: NTS	THIRD ANGLE	Unstated .X XX	Tolerances: N/A N/A	Material	
Drawn: NYW	$\rightarrow$	.XXX ANGLES	N/A N/A	SEE NOTE	
App'd: XXX	Title CABLE ASSEMBLY N		NOT TO SCALE		
Date: 13 JUN. '23	Revision: 1.3			Unit: mm	Г



Type: Cable 355 RF

CABLE 355 RF

DI awing Number	ullibel :			
Sheet 1	of 1			
Drawing (C)	E and O E			