

## CABLE 207 RF: RF CABLE ASSEMBLY, I-PEX MHF IV L PLUG + FME S/T BULKHEAD PLUG WITH O-RING + 1.13MM CABLE

## SPECIFICATIONS:

- 1. I-PEX MHF IV L PLUG (20565-001R-13).
- 2. Ø1.13MM COAXIAL CABLE, COLOR: GRAY
- 3. FME STRAIGHT BULKHEAD PLUG WITH 0-RING, P/N: RFCT-FMF002-M78

## NOTES:


- 1. THE ORIENTATION OF CONNECTORS ON DRAWING IS FOR REFERENCE ONLY, IF THE ORDER IS LEFT BLANK THE CONNECTOR WILL NOT HAVE FIXED ORIENTATION.
- 2. FIXED ORIENTATION IS SUGGESTED FOR CABLE LENGTH 25MM TO 100MM. PLEASE SPECIFY THE FIXED ORIENTATIONS FROM THE ORDER CODE (F1, F2, ETC)
- 3. CONTACT GRAD CONN IF THE ORIENTATION YOU REQUIRE IS NOT SHOWN.
- 4. WORKING FREQUENCY RANGE: DC-3GHz
- 5. OPERATING TEMPERATURE: -40°C TO +85°C.
- 6. IMPEDANCE: 50 OHM.


## USAGE PRECAUTIONS: CABLES USING 'MICRO' COAX ARE DELICATE:

(i) HANDLE WITH CARE.

(ii) DO NOT TWIST; APPLY EXCESSIVE FORCES OR SHARP BENDS TO THE CABLE. DO NOT FORCEFULLY DEFORM WIRES.

(iii) CONSULT CONNECTOR MANUFACTURER'S DATASHEETS FOR DETAILED NOTES ON HANDLING INSTRUCTIONS.







"L" LENGTH IN MM
eg: 100MM = 100
(MIN. 025-MAX.400
STANDARD = 100, 150, 200)
Tolerance: <50mm: ±2mm.
51-200mm: ±5mm.

O-RING, WASHER AND NUT OPTIONS: BLANK = SEPARATELY PACKED (STANDARD) A = ALL ASSEMBLED WITH CONNECTOR

 $2 = \phi 1.13MM$  CABLE, COLOR: GRAY


ORIENTATION OPTIONS:

201-400mm: ±7mm. BLANK = DOES NOT HAVE A FIXED ORIENTATION

F1 = MHF CONNECTION DOWN (L=25-220MM)

F2 = MHF CONNECTION UP (L=25-220MM)

(SEE NOTES 1, 2, 3 AND DIAGRAMS FOR MORE INFORMATION)



\$10.25

RECOMMENDED FME
MOUNTING HOLE

EV. DATE & DRN	0 19/05/*15 - NYW RELEASE	29/04/"16 – NYW REMOVE 0.81 CABLE OPTION. ADD 1.13 CABLE OPTION.	2 08/04/'22 - NYW UPDATE FME P/N. ADD NOTES 5 & 6.	
≳	_		~ ~	

Scale: NTS	THIRD ANGLE	Unstated Tolerances: .X ±0.2 .XX ±0.1	Material SEE NOTE
Drawn: NYW	$\bigoplus$	.XXX ±0.05 ANGLES ±5	SEE NOTE
App'd: XXX	Title CABLE ASSEMBLY  Revision: 1.2		NOT TO SCALE
Date: 8 APR. '22			Unit: mm



Type: Cable 207 RF

CABLE 207 RF

Drawing Number:

Sheet 1	of 1
Drawing (C)	E and O E