COAXIAL CABLE ASSEMBLY

CABLE 283 RF: MMCX R/A PLUG + RP SMA STRAIGHT BULKHEAD JACK WITH 0-RING RATED TO IP67/68 + MULTIPLE CABLE SIZES

RoHS Compliant

SPECIFICATIONS:


- 1. MMCX RIGHT ANGLE PLUG. P/N: FOR RG178 CABLE: RFCT-MMCX003-M78 FOR Ø1.32MM CABLE: RFCT-MMCX005-M32
- 2. COAXIAL CABLE. SEE P/N OPTIONS
- 3. RP SMA STRAIGHT BULKHEAD JACK WITH 0-RING RATED TO IP67/68. P/N: RFCT-SMA008-F78. GOLD

ENVIRONMENTAL:

- A. BULKHEAD MOUNTED CONNECTOR (RFCT-SMA002-F78) TESTED TO THE FOLLOWING SPECIFICATION:
- i. IP6X DUST TIGHT NO PARTICLE INGRESS.
- ii. IPX7 WATERPROOF FOR 30 MINUTES UP TO 1 METER UNDERWATER.
- iii. IPX8 WATERPROOF FOR 48 HOURS AT 1 METER UNDERWATER.
- iv. IPX8 WATERPROOF FOR 12 HOURS AT 5 METERS UNDERWATER.
- v. PRESSURE TEST 1 BAR FOR 10 SECONDS.

NOTES:


- 1. THE ORIENTATION OF CONNECTORS ON DRAWING IS FOR REFERENCE ONLY. IF THE ORDER IS LEFT BLANK THE CONNECTOR WILL NOT HAVE FIXED ORIENTATION.
- 2. FIXED ORIENTATION IS SUGGESTED FOR CABLE LENGTH 50MM TO 100MM. PLEASE SPECIFY THE FIXED ORIENTATIONS FROM THE ORDER CODE (F1. F2. ETC)
- 3. CONTACT GRAD CONN IF THE ORIENTATION YOU REQUIRE IS NOT SHOWN.
- 4. WORKING FREQUENCY RANGE: DC-3GHz
- 5. OPERATING TEMPERATURE: -40°C TO +80°C
- 6. IMPEDANCE: 50 OHM



USAGE PRECAUTIONS: CABLES USING 'MICRO' COAX ARE DELICATE:


- (i) HANDLE WITH CARE.
- (ii) DO NOT TWIST: APPLY EXCESSIVE FORCES OR SHARP BENDS TO THE CABLE. DO NOT FORCEFULLY DEFORM WIRES.
- (iii) CONSULT CONNECTOR MANUFACTURER'S DATASHEETS FOR DETAILED NOTES ON HANDLING INSTRUCTIONS.








DETAIL A





RP SMA DETAIL DRAWING

HOW TO ORDER CABLE 283 RF - <u>X X X X - X X - X</u> - <u>X</u>

"L" LENGTH IN MM: eg: 100MM = 0100

(MIN. 0050-MAX.2000

STANDARD = 0100, 0150, 0200)

Tolerance: <50mm: +2mm.

51-200mm: ±5mm. 201-500mm: ±7mm.

>501mm: ±10mm.

CABLE SIZE OPTIONS:

1 = RG178 CABLE, COLOR: BROWN. $2 = \emptyset 1.32MM$ CABLE, COLOR: GRAY

WASHER AND NUT OPTIONS:

BLANK = SEPARATELY PACKED (STANDARD)

A = ALL ASSEMBLED WITH CONNECTOR


ORIENTATION OPTIONS:

BLANK = DOES NOT HAVE A FIXED ORIENTATION

F1 = MMCX CONNECTION DOWN (L=50-100MM)

F2 = MMCX CONNECTION UP (L=50-100MM)

(SEE NOTES 1, 2, 3 AND DIAGRAMS FOR MORE INFORMATION)



Scale:	NTS	THIRD ANGLE	Unstated Tolerances: .X N/A .XX N/A	Ī
Drawn	: CC	\bigoplus	- XXX N/A ANGLES N/A	
App'd:	XXX	Title CABLE ASSEMBLY		
Date:	10 MAR '24	Revision: 1.2	Unit: mm	H





Type: Cable 283 RF CABLE 283 RF Drawing Number

(C) THIS DRAWING IS CONFIDENTIAL AND MUST NOT BE COPIED OR DISCLOSED WITHOUT WRITTEN CONSENT

Sheet 1 of 1 Drawing (C) E and 0 E